

Century® Air Compressor OEM Special Replacement Motors

OEM Special Replacements – Dripproof – Rigid Base – Single Phase Capacitor Start/Capacitor Run



B385

Features:

Non-Reversible–Connected for CW Facing End Opposite Shaft • Energy Efficient \$ • 60 HZ • 40°C Ambient • Class B Insulation • Manual Protector

HP	RPM	Volts	Full Load Amps	Service Factor	Frame	Stock Number	Sears Part Number	“C” Dim.	Notes
2 SPL	3600	115/230	15.0/7.5	1.0	56	B381		11.3	\$
3 SPL	3600	115/230	15.0/7.5	1.0	56	B383		11.6	\$
5 SPL	3600	208-230	15.0	1.0	56	B385		12.6	\$
SPL	3600	230	16.6		56H	B215	M0706	113.4	\$

Air Compressor Motors

Rigid Base – 3600 & 1800 RPM – 1/2 thru 6 HP Single Phase

Features:

- Ball Bearings
- 60 Hz
- Class B or F Insulation
- 40°C Ambient
- Continuous Duty
- Rigid Base
- Open Construction



CP1152L

B813

Applications: Designed for air compressor loads. May be suitable for other applications having similar loads.

HP	RPM	Volts	Full Load Amps	Service Factor	Frame	Stock Number	Overload Protector	Rotation	Insulation Class	“C” Dim	Efficiency	Notes
1/2	3600	115/230	9.6/4.8	1.00	56	B685	Manual	CWLE	B	11.0		
3/4	3600	115/230	12.5/6.75	1.00	56	CP1072L	Manual	REV	B	10.6		
1	3600	115/230	12.0/6.0	1.00	56	CP1102L	Manual	REV	B	11.4		
1-1/2	3600	115/230	12.5/6.3	1.00	56	CP1152L	Manual	REV	B	11.9		85,\$
2	3600	115/230	22.2/11.1	1.00	56	CP1202L	Manual	REV	B	12.7		
		208/230	13.1/12.3	1.00	56	CP1302L	Manual	REV	B	12.7		85,\$
3	3600	230	15.0	1.00	56	B812	Manual	CWLE	B	12.1		1,85,\$
		115/230	34.0/17.0	1.15	184T	V201	None	REV	B	14.7	77.0	
5	3600	230	19.7	1.00	56HZ	CP1502L	Manual	REV	B	14.1		15,85,\$
		230	22.0	1.00	56HZ	B813	Manual	CWLE	B	14.1		85,\$
		208-230	22.0	1.15	56HZ	B386	Manual	CWLE	B	14.6		85,\$
		208-230	22.0	1.15	56Y	B384	Manual	CWLE	B	14.6		85,97,320,\$
		230	25.6	1.15	184T	V211	None	REV	B	14.7	77.0	
6	3600	230	24.0	1.00	184T	V208	None	REV	F	15.0	82.0	85,\$
SPL	3450	230	15.0	1.00	56Y	B387	Manual	CWLE	B	14.6		85,97,298,\$
SPL	3450	230	15.0	1.00	56H	CP1502LV1	Manual	REV	B	12.8		85,180,\$

Notes:

- Item to be discontinued when stock is depleted
- 56HZ = 7/8" x 2-1/4" Shaft
85. Energy efficient \$ - capacitor start/run
97. 182T and 184T mounting holes, 4.5" shaft height
180. Low AMP replacement for a variety of O.E.M. "Special" and "SPL 5" horsepower requirements
298. 2-1/4" x 7/8" keyed shaft
320. 56Y = 7/8" diameter keyed shaft, 2.25" long

