

F2-D.500-20D

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2000		947 / 0.47	1161 / 0.82	1344 / 1.25	1506 / 1.72	1650 / 2.23	1781 / 2.76	1899 / 3.29	2008 / 3.82
2500		1070 / 0.70	1264 / 1.10	1431 / 1.55	1582 / 2.05	1722 / 2.61	1852 / 3.21	1972 / 3.84	2083 / 4.48
3000	957 / 0.52	1199 / 1.01	1380 / 1.47	1535 / 1.96	1674 / 2.49	1805 / 3.07	1928 / 3.70	2044 / 4.37	2154 / 5.07
3500	1116 / 0.83	1333 / 1.40	1504 / 1.95	1649 / 2.49	1780 / 3.07	1902 / 3.68	2017 / 4.33	2128 / 5.02	2232 / 5.75
4000	1276 / 1.23	1470 / 1.88	1632 / 2.52	1770 / 3.14	1894 / 3.77	2009 / 4.42	2118 / 5.11	2222 / 5.83	2322 / 6.59
4500	1434 / 1.76	1610 / 2.48	1764 / 3.22	1896 / 3.92	2014 / 4.62	2125 / 5.33	2228 / 6.06	2326 / 6.81	
5000	1594 / 2.41	1755 / 3.22	1899 / 4.04	2025 / 4.83	2139 / 5.61	2244 / 6.38	2344 / 7.17		
5500	1753 / 3.21	1900 / 4.09	2036 / 5.00	2158 / 5.89	2267 / 6.75				
6000	1913 / 4.16	2048 / 5.11	2175 / 6.11	2292 / 7.09					

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00152ET3E182T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3E184T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3H184T-W22 has an rpm range of 800 to 1150.
- Motor 00212OT3H184T-S has an rpm range of 800 to 1150.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor DHP0026 has an rpm range of 800 to 1150.
- Motor DTP0016 has an rpm range of 800 to 1150.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0026-50 has an rpm range of 800 to 958.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP1/54 has an rpm range of 800 to 1750.
- Motor DTP1/56 has an rpm range of 800 to 1150.
- Motor DTP1/56-50 has an rpm range of 800 to 958.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor EP0026 has an rpm range of 800 to 1150.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP0026 has an rpm range of 800 to 1150.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor GP1/54 has an rpm range of 800 to 1800.
- Motor GP1/56 has an rpm range of 800 to 1150.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP0026 has an rpm range of 800 to 1150.
- Motor NP0034 has an rpm range of 800 to 1755.
- Motor NP0054 has an rpm range of 800 to 1745.
- Motor NP1/54 has an rpm range of 800 to 1730.

Max listed CFM for Recirculating Direct Fired Heaters : A2 = 5000